



MFP	<b>TECHNICAL TIP</b>
<b>TT-20150</b>	

**Models:** ALL SHARP MFPS

**Priority:** Medium

**Date:** February 2010

**Subject:** Sharp MFPs and CITRIX Compatibility

**Description:** This is a compatibility statement regarding Sharp MFPs and Citrix.

**Details:** Please see the following pages for more information regarding Sharp MFPs and Citrix.

## **SHARP MFPs and CITRIX<sup>®</sup>** **COMPATIBILITY STATEMENT**

This Document provides a compatibility statement for Sharp's MFPs and their print drivers within Citrix & Microsoft<sup>®</sup> environments

Sharp MFPs offer both standard and optional hardware that is modular and scalable addressing a wide variety of networks and printing environments. Sharp MFPs include Digital copiers, multi-functional peripherals-MFP (Print, Copy, Scan and Fax) and network printers.

The following Sharp MFPs and associated print drivers are compatible with Citrix XenApp5.0, Citrix Metaframe, Citrix Presentation Server (ver. 4.0 & ver. 4.5) and Terminal Services environments.

**Sharp MFPs that are CITRIX Compatible for the following Citrix environments:**

**Table 1 for: XEnAPP5.0, Metaframe, Presentation Server and Terminal services**

Model	Speed-ppm	Comments
MX-C311/C401	31/40 B&W and color	*3, *4
DX-C310/C400	31/40 B&W and color	*3, *4
DX-C311/C401	31/40 B&W and color	*3, *4
MX-2600N/3100N	26/31 B&W and color	*3, *4
MX-4100N/5000N	41/50 B&W and color	*2, *4
MX-2300N/2700N	23/27 B&W and color	*1, *2, *4
MX-3500N/3501N/4501N	35/35/45 B&W and 35 color	*1, *2, *4
MX-5500N/6200N/7000N	55/62/70 B&W and 41 color	*1, *2, *4
MX-6201N/7001N	62/70 B&W and 50 color	*2, *4
MX-M283/M363/M453/M503	28/36/45/50 B&W	*3
MX-B401	40 B&W	*3

**Table 2 for: Metaframe, Presentation Server and Terminal services**

Model	Speed-ppm	Comments
AR-M257/M317	25/31 B&W	*1
MX-M350N/M450N	35/45 B&W	
MX-M550N/M620N/M700N	55/62/70 B&W	
MX-M850N/M950N/M1100N	85/95/110 B&W	*2, *1
AR-208D	20 B&W	
AR-M237/M277	23/27 B&W	
AR-M350/P350/M450/P450	35/45 B&W	
AR-M355/M455	35/45 B&W	
AR-M550/M620/M700 series	55/62/70 B&W	*1

\*1) Settings of paper source or paper output tray will return to their default settings ( "Auto Select") after each log in.

\*2) Tandem Print cannot be used in all Citrix environments

\*3) Tandem Print cannot be used in XEnAPP5.0 environments

\*4) Driver Duplication feature is not supported in XEnAPP5.0 environments

### Evaluated Environment

Server Environment	OS: Windows Server 2008 Enterprise 32 bit
	Citrix application: <b>XenApp 5.0 32bit</b>
	Server side driver: PCL6 32 bit driver
Client OS	WindowsXP Professional SP3 32bit and Windows Vista Ultimate SP1 32 bit

### Evaluated Environment

Server Environment	OS: Windows Server 2008 Enterprise 64 bit
	Citrix application: <b>XenApp 5.0 64bit</b>
	Server side driver: PCL6 64 bit driver
Client OS	WindowsXP Professional SP3 64bit and Windows Vista Ultimate SP1 64 bit

### Evaluated Environment

MetaFrame Server	OS: Windows Server 2000
	Citrix application: <b>Citrix MetaFrame XP</b> for Windows with <b>Feature Release 3</b>
	Server side driver: Same as XP client driver
Client OS	Windows98SE, WindowsNT4.0 Workstation, Windows XP Professional 32bit

### Evaluated Environment

Server Environment	OS: Windows Server 2003 32 bit
	Citrix application: <b>Citrix Presentation Server 4.0</b>
	Server side driver: Same as XP client driver
Client OS	Windows98SE, WindowsNT4.0 Workstation and Windows XP Professional 32bit

### Evaluated Environment

Server Environment	OS: Windows Server 2003 SP2 32 bit
	Citrix application: <b>Citrix Presentation Server 4.5 with Feature Pack 1</b>
	Server side driver: Same as XP client driver
Client OS	WindowsNT4.0 SP6, WindowsXP Professional SP2/SP3 32bit and Windows Vista SP1 32 bit

Sharp is a registered trademark of Sharp Corporation. All other trademarks and registered trademarks are the property of their respective owners. Sharp does not warrant or grant that any of the information contained herein pertaining to any third parties is accurate or complete. Sharp is not responsible for or does not endorse the contents of any third party linked sites. Design and Specifications are subject to change without notice.